

# BRM-1

remote-control unit

M O O N

by SIMAUDIO

## Contents

A new remote-control experience .....	2
Explore new frontiers.....	4
Before getting started.....	5
Get to know your MOON BRM-1 .....	6
Pair your MOON BRM-1 .....	7
Operate your MOON BRM-1 .....	8
Common Functions.....	8
Additional Functions.....	8
Care for your MOON BRM-1.....	9
Technical.....	10
specifications.....	10

---

## A new remote-control experience

The MOON BRM-1 represents a revolution in remote-control design, an innovative concept of form and function. Now, you can experience the luxurious feel of the exquisitely crafted MOON volume knob from wherever you enjoy your music. With its ground-breaking touch controls, visual feedback, and lavish refinement, the MOON BRM-1 sets the new standard for a premium audio system remote control.

---

## Explore new frontiers

The landmark North Collection represents the culmination of years of research and development in the fields of audio, electronics, materials, and manufacturing processes. Its exciting new look is surpassed only by improvements in performance made possible by the passionate team of Simaudio engineers and technicians dedicated to delivering an uncompromised music listening experience. With the purchase of this MOON product, you join an elite group of music lovers around the world who expect the absolute best performance and build quality from products in any class.

Get ready for the performance of a lifetime.

---

## Before getting started...

Carefully remove the unit from its packaging. Visually inspect it and report any damage to your MOON Retailer immediately.

The packaging materials were designed to protect this product while in transit. Store these materials with the rest of the packaging.

The information contained in this Guide is subject to change without notice. The most recent version is available at [simaudio.com/guides-downloads](https://simaudio.com/guides-downloads).

This device features a power switch (I/O) on its underside. The switch is in the Off position by default. This is necessary when the device is in transit. For normal use, toggle the switch to the On position. Do not even switch off the power to charge the battery.

---

## Get to know your MOON BRM-1

The MOON BRM-1 may be held or set on a flat surface. Since it is unnecessary to aim this remote-control unit at a device to control it, it may be placed virtually anywhere in the room or beyond.

The remote-control unit is powered by a rechargeable lithium-ion battery. Connect a USB cable to the USB-C connector on the underside of the unit and leave the power switch in the **On** position to charge it with a standard USB charger.

The unit comprises three distinct sections.

1. The outer ring serves to adjust volume and to select inputs on linked devices.
2. Four virtual buttons appear around the perimeter of the display to control the most common functions of a MOON network player and preamplifier: **Play/Pause**, **Forward**, **Back**, and **Mute**.
3. The centre of the display indicates the volume level of the linked device, the active input, and additional functions.



*When the BRM-1 is powered on but not linked with a MOON device, it displays its unique ID. This occurs prior to configuration, when the remote control is out of range of the device, or when the device is powered off.*

---

## Pair your MOON BRM-1

Any MOON BRM-1 could control any compatible MOON device. To establish a link between the MOON BRM-1 and a specific device, enter the [Setup](#) menu on the corresponding device, and select Remote Control.

- Link Remote searches for a nearby MOON BRM-1 remote control, displaying its ID on both devices and permitting them to be associated.
- Unlink Remote displays associated MOON BRM-1 units permitting them to be disassociated from this device.
- Information displays useful information about the associated MOON BRM-1 units.


## Operate your MOON BRM-1

The power switch must remain **On** when in use or asleep, and when charging the battery.

The MOON BRM-1 has two sets of functions.

### Common Functions







Tapping quickly in the centre of the display toggles between **Volume** and **Input** modes.



The rotating knob mimics the behaviour of the rotary knob on the linked MOON device.

### Additional Functions

Holding a finger for two seconds in the centre of the display toggles between **common** and **additional** functions. The **Play/Pause** and **Mute** buttons scroll forward and backward through five screens.

-  *toggles the linked MOON device into or out of **Standby**, as well as all devices in its MOONLink Group*
-  *adjusts the **Balance** of the linked MOON device using the rotary knob*
-  *adjusts the **Brightness** of the BRM-1 display*
-  *monitors the **Battery Level** of the BRM-1*  
*Recharge the battery when the Battery level is depleted: *
-  *reveals the **ID** of the BRM-1*



---

## Care for your MOON BRM-1

Avoid cleaning products. A dry micro-fibre cloth or a cloth for cleaning eye glass lenses should suffice.

---

## Technical specifications

<b>Coverage</b>	30 m / 100'
<b>Battery Life</b>	25 h
<b>Charging Time</b>	2 h
<b>Dimensions</b>	110.7 mm x 79.2 mm x 63.7 mm / 4.4" x 3.1" x 2.5"
<b>Weight</b>	272.2 g / 0.6 lbs